

Mit dem Kauf der SANlight EVO LED-Leuchte haben Sie sich für ein hochwertiges Produkt entschieden, welches Ihnen viel Freude bereiten wird. Bitte lesen Sie die Betriebsanleitung bevor Sie Ihre EVO LED-Leuchte in Betrieb nehmen, da durch falsche Verwendung Schäden an der Leuchte oder an Menschen/Tieren/Pflanzen entstehen können. Bei nicht fachgerechter Verwendung der EVO erlischt jeglicher Garantieanspruch sowie die Produkthaftung des Herstellers.

Gültig für die Modelle **EVO 3-60, EVO 3-80, EVO 3-100, EVO 4-80, EVO 4-100, EVO 4-120, EVO 5-100, EVO 5-120, EVO 5-150, EVO 6-120, EVO 6-150** welche als **EVO** bezeichnet werden.

Abstand zu belichtetem Objekt

Der Abstand zwischen Leuchte (Unterkannte der Leuchte) und der belichteten Fläche bzw. des belichteten Objekts muss mindestens 15cm betragen.

Anwendungsbereich der Leuchte

Die Leuchte SANlight EVO ist ausschließlich für die Belichtung von Pflanzen, auch in feuchten Innenräumen, geeignet.

Zulässige Umgebungstemperatur für den Betrieb

Die Leuchte SANlight EVO darf bis zu einer maximalen Umgebungstemperatur von 35°C betrieben werden. Die minimale Umgebungstemperatur, bei der die Leuchte SANlight EVO betrieben werden darf, liegt bei 5°C.

Zulässige Umgebungsbedingungen für den Betrieb

Die Leuchte SANlight EVO darf bis zu einer relativen Luftfeuchtigkeit von max. 90% (nicht kondensierend) betrieben werden.

Benötigtes Zubehör zum Aufhängen der Leuchte

Im Lieferumfang ist kein Aufhängezubehör enthalten. Die Leuchte EVO darf nur mit ausreichend tragfähigen Aufhängungen aufgehängt werden. Es wird empfohlen, dass die Leuchten mittels Stahlkarabinern und Seilen an den Aufhängeösen aufgehängt wird. (siehe Abbildungen 1, 2 und 3) Eine Aufhängung muss mindestens eine Dauerbelastung von 8kg aushalten.

Zulässige Orientierung der LED-Leuchte

Die LED-Leuchte SANlight EVO darf nur in waagrecht aufgehängter Lage betrieben werden. Dabei ist ein Mindestabstand zu umgebenden Objekten von 15cm einzuhalten. Um die korrekte Lage zu garantieren, muss die Leuchte an beiden Aufhängeösen aufgehängt werden. (siehe Abbildungen 1 und 2) Die Leuchte darf auch über die äußeren Aufhängeösen abgehängt werden, um eine Schräglage der Leuchte zu erreichen. Siehe Abbildung 3.

Verlegen der Kabel

Achten Sie bei der Verlegung von Kabeln darauf, dass diese zugentlastet sind. Die Kabel dürfen auf keinen Fall unter Spannung gesetzt werden. Die Kabel müssen abgewickelt werden. Die EVO Leuchte darf nicht mit aufgerollten Kabeln betrieben werden. Achten Sie darauf, dass sie nicht verdeckt oder durch eine Wand, den Boden, die Decke oder andere Gebäudeteile geführt werden. Verlegen Sie die Kabel auch nicht oberhalb einer abgehängten Decke und stellen Sie sicher, dass sie nicht dauerhaft an der Gebäudestruktur befestigt sind. Beachten Sie, dass sie so verlegt werden, dass sie keiner Belastung ausgesetzt sind und vor physischen Schäden geschützt sind. Außerdem müssen die Kabel auf ihrer gesamten Länge sichtbar sein. Beachten Sie, dass die maximale Umgebungstemperatur für den Betrieb der EVO LED-Leuchte mit dem Kabel 35°C beträgt.

Instandhaltung und Reinigung

Für die Reinigung der LED Leuchte ist ein staub- und fettfreies Tuch zu verwenden. Für die Reinigung muss die Leuchte vom allgemeinen Stromnetz getrennt werden. Verwenden Sie keinesfalls andere Hilfsmittel wie Reiniger, feuchte Tücher etc. Achten Sie darauf, dass die Sekundäroptik der LEDs durch das Reinigen nicht verkratzt wird.

Arbeiten und Reparaturen

Reparaturen und Arbeiten dürfen nur vom Hersteller durchgeführt werden. Bei Reparaturen, Modifikationen und anderen Arbeiten, welche nicht vom Hersteller oder einem von ihm beauftragten Servicetechniker oder einer vergleichbar qualifizierten Person durchgeführt werden, erlöschen die Herstellergarantie sowie die Produkthaftung.

Upgrade-Service

Die einzelnen LED-Module können von Fachpersonal getauscht werden. Wenden Sie sich dazu bitte an den zertifizierten SANlight Händler Ihres Vertrauens.

Garantieerklärung

Dieses Gerät wurde nach der europäischen Sicherheitsnorm (EN60598/CE) entworfen, hergestellt und geprüft. Die Garantie für die LED Leuchte sowie das Zubehör beträgt 3 Jahre ab Kaufdatum. Die Garantie gilt nicht für Geräte, die nicht entsprechend den Vorgaben in dieser Anleitung installiert, verwendet und gewartet wurden. Der Hersteller übernimmt keine Verantwortung für Schäden, welche durch unautorisierten oder falschen Gebrauch verursacht wurden.

Im Schadensfall ist das Gerät (LED Leuchte inkl. Anschlusskabel) an den jeweiligen SANlight Vertriebspartner zurückzugeben, bei welchem das Produkt erworben wurde. Dieser sendet die defekte Ware an den Hersteller SANlight. Nach erfolgter Reparatur durch den Hersteller wird das Gerät wieder an den jeweiligen Vertriebspartner übergeben.

ACHTUNG fotobiologischer Sicherheitshinweis:

Nach DIN EN 62471 wird das LED-Modul der EVO in die Risikogruppe „Exempt“ eingeteilt. Diese photobiologische Sicherheitskennzeichnung beruht auf der Prüfung der Lichtleistungscharakteristik einer einzelnen Gartenbauleuchte. Ein erhöhtes Expositionsrisiko für das Personal der Einrichtung kann, abhängig von der Anzahl der Gartenbauleuchten und deren Anordnung und/oder Positionierung innerhalb der Pflanzenzuchtanlage, vorhanden sein. Es liegt in der Verantwortung der Pflanzenzuchtanlage, diese Risiken auf der Ebene der Anlage zu behandeln und diese anzugehen sowie sicherzustellen, dass Personen, die die Pflanzenwachstumsbereiche bei eingeschalteter Beleuchtung betreten, sich dieser Risiken bewusst sind und das geeignete Sicherheitsvorkehrungen getroffen werden. **Vermeiden sie trotzdem unnötig lange Bestrahlung und den direkten Blick in die Lichtquelle.**

Gefahrenhinweise

ACHTUNG: Der Mindestabstand zu Objekten in der Umgebung der LED-Leuchte beträgt 15cm. Der Kühlkörper/das Gehäuse darf nicht abgedeckt werden. **ACHTUNG:** Die EVO LED-Leuchte ist ausschließlich für die Belichtung von Pflanzen, auch in feuchten Innenräumen, geeignet. **ACHTUNG:** Nicht direkt in die Lichtquelle blicken. **ACHTUNG:** Nicht in explosionsgefährdeter Umgebung betreiben. **ACHTUNG:** Die EVO LED-Leuchte darf bei maximaler bestimmungsgerechter Umgebungstemperatur (35°C) bis zu 70°C heiß werden. **ACHTUNG:** Die LED-Leuchte muss ausreichend gegen Herunterfallen gesichert werden. **ACHTUNG:** Wird ein Schaden an der LED-Leuchte oder an einem Kabel festgestellt, so ist die Leuchte unverzüglich außer Betrieb zu nehmen. Dies muss durch die Trennung der Leuchte vom allgemeinen Stromnetz erfolgen. **ACHTUNG:** Zur Vermeidung von Gefährdungen darf eine beschädigte äußere flexible Leitung dieser Leuchte ausschließlich vom Hersteller, seinem Servicevertreter oder einer vergleichbaren Fachkraft ausgetauscht werden. **ACHTUNG:** Die Lichtquelle kann nicht separat bezogen werden. **ACHTUNG:** Zum Schutz vor Verletzungen ist bei Arbeiten im Bereich der Leuchte entsprechende persönliche Schutzausrüstung (PSA) zu tragen. **ACHTUNG:** Die Modelle der EVO-Serie sind NICHT für das Durchschleifen der netzseitigen Stromversorgung ausgelegt.

Lieferumfang

Abbildung 4 zeigt alle Komponenten Ihrer EVO LED-Leuchte am Beispiel einer EVO 5-120. Prüfen Sie bitte den Inhalt der Verpackung auf Vollständigkeit und Beschädigung. Verwenden Sie keinesfalls beschädigte Komponenten. Das netzseitige Anschlusskabel ist nicht enthalten und kann bei Ihrem Händler separat geordert werden. Im Lieferumfang sind enthalten: 1 x LED-Leuchte EVO, Betriebsanleitung.

Installations- und Montageanweisung

Befestigung und Aufhängung der Leuchte SANlight EVO:

Die EVO LED-Leuchte kann an den Aufhängeösen aufgehängt werden (siehe Abbildungen 1, 2 und 3). Beim Aufhängen der Leuchte EVO ist ein Sicherheitsabstand von 15cm zu umgebenden Objekten einzuhalten. Achten Sie auf den sicheren Sitz Ihrer Aufhängung und sichern Sie die Leuchte ausreichend gegen unbeabsichtigtes Herunterfallen.

Elektrischer Anschluss der EVO:

Die EVO Leuchte darf nur mit dem separat erhältlichen Anschlusskabel (siehe Tabelle 1) am Stromnetz angeschlossen werden. Es ist möglich jede Leuchte separat anzuschließen oder mehrere Leuchten parallel miteinander zu verbinden. Dazu dürfen nur die Kabel des Herstellers SANlight verwendet werden. Der Anschluss der EVO LED-Leuchte an das Stromnetz muss durch eine qualifizierte Elektrofachkraft unter Berücksichtigung der lokalen Installationsvorschriften vorgenommen werden. Die EVO LED-Leuchte darf nicht auf feuchtem und leitendem Untergrund installiert werden.

Anschluss einer EVO Leuchte:

Folgende länderspezifische Kabel dürfen zum Anschluss einer EVO Leuchte ans Stromnetz verwendet werden.

	SANlight Artikelnummer	Bezeichnung	Eigenschaften	Anschluss
Tabelle 1	AI0037	Netzanschlussleitung EVO-Serie EU	2m PVC 1,5mm ² schwarz	Schuko Anschlussstecker
	AI0038	Netzanschlussleitung EVO-Serie UK	2m PVC 1,5mm ² schwarz	UK Anschlussstecker
	AI0039	Netzanschlussleitung EVO-Serie CH	2m PVC 1,5mm ² schwarz	Schweizer Anschlussstecker SEV1011
	AI0040	Netzanschlussleitung EVO-Serie US	2m PVC 1,5mm ² schwarz	US Anschlussstecker NEMA 5-15 P

Für den Anschluss einer EVO Leuchte an das allgemeine Stromnetz ist die länderspezifische Netzanschlussleitung von SANlight zu verwenden. Verbinden sie zuerst das Anschlusskabel mit der Leuchte, bevor Sie diese am allgemeinen Stromnetz anschließen.

Anschluss mehrerer Leuchten	Absicherung der Netzleitung	Max. Anzahl der Leuchten pro Sicherungsautomat
Je nach Absicherung der Versorgungszuleitung können mehrere Leuchten miteinander elektrisch verbunden werden. Bitte beachten Sie dazu die Tabelle 1.	Sicherungsautomat Typ B 230V	4 Leuchten
	Sicherungsautomat Typ C 230V	7 Leuchten

Sollen mehr als 7 Leuchten an einem Sicherungsautomaten betrieben werden, so ist die Verwendung eines Einschaltstrombegrenzers erforderlich. Um mehrere Leuchten an einer Steckdose zu betreiben sind folgende Komponenten erforderlich.

SANlight Artikelnummer	Bezeichnung	Anzahl
AI0037 / AI0038 / AI0039 / AI0040	Netzanschlussleitung EVO länderspezifisch 2m PVC 1,5mm ² schwarz	1
AI0018	H Verteiler	1 Stück für je 2 Leuchten
AI0022	Verlängerungsleitung Buchse - Stecker 1m PVC 1,5mm ² schwarz	1 Stück pro Leuchte

ACHTUNG: Der Anschluss von mehreren Leuchten über ein Versorgungskabel darf nur von geschultem Fachpersonal durchgeführt werden. Wenden Sie sich dazu an Ihren zertifizierten SANlight Handelspartner. Eine detaillierte Anschlussanleitung finden sie auf unserer Homepage unter www.sanlight.com.

Technische Daten EVO 3-60, EVO 3-80 und EVO 3-100	Technische Daten EVO 4-80, EVO 4-100 und EVO 4-120		
Netzseitige Leistungsaufnahme	200W	Netzseitige Leistungsaufnahme	265W
Eingangsspannung	220-240V~ 50/60Hz	Eingangsspannung	220-240V~ 50/60Hz
Zulässige Umgebungstemperatur	5-35°C	Zulässige Umgebungstemperatur	5-35°C

Technische Daten EVO 5-100, EVO5 -120 und EVO 5-150	Technische Daten EVO 6-120 und EVO 6-150		
Netzseitige Leistungsaufnahme	340W	Netzseitige Leistungsaufnahme	400W
Eingangsspannung	220-240V~ 50/60Hz	Eingangsspannung	220-240V~ 50/60Hz
Zulässige Umgebungstemperatur	5-35°C	Zulässige Umgebungstemperatur	5-35°C

Position Tc Messpunkt siehe Abbildung 5.	Technische Daten eines einzelnen LED-Modules	
	Betriebsstrom	0,73A (DC)
	Nennleistung	63W
	Nennspannung	86V (DC)
	Tc	105°C



Achtung: Nicht direkt in die Lichtquelle blicken.

“照明器具を長時間見続けることがないように照明器具を設置すること”



Die LED-Leuchte darf nicht im Haushaltsmüll entsorgt werden! Zur Entsorgung kann die Leuchte beim Hersteller abgegeben werden. Die Entsorgungskosten übernimmt der Hersteller. Alternativ kann die Leuchte bei einem Entsorgungsbetrieb für Elektrogeräte abgegeben werden.



Achtung: Die Leuchte ist nicht dazu geeignet, abgedeckt zu werden!



Vorsicht, Gefahr des elektrischen Schlags

IP65

Staubdicht und geschützt gegen Strahlwasser aus einem beliebigen Winkel.



Die Lichtquelle bzw. das LED-Modul dieser Leuchte darf nur vom Hersteller oder einem von ihm beauftragten Servicetechniker oder einer vergleichbar qualifizierten Person ersetzt werden.



Abbildung 1



Abbildung 2



Abbildung 3



Abbildung 4




Abbildung 5

Kontakt Hersteller: SANlight GmbH, Montafonerstrasse 14, 6780 Schruns, Austria, www.sanlight.com, support@sanlight.com

Viel Erfolg bei der Verwendung Ihrer Leuchte. Für Fragen, Anregungen oder weitere Informationen wenden Sie sich bitte an Ihren Händler oder an uns.

By purchasing the SANlight EVO LED-light you have decided on a high-quality product, which will give you much pleasure. Please read the operating instructions before using your EVO LED-light, as incorrect use can cause damage to the light or to humans/animals/plants. Failure to use the EVO properly will void any manufacturer's warranty and product liability.

Valid for **EVO 3-60, EVO 3-80, EVO 3-100, EVO 4-80, EVO 4-100, EVO 4-120, EVO 5-100, EVO 5-120, EVO 5-150, EVO 6-120, EVO 6-150** further denoted as **EVO**.

ATTENTION: Photobiological safety note:

According to DIN EN 62471, the EVO LED-module corresponds to risk group "exempt". These photobiological safety markings are based on testing of the light output characteristic of a single horticultural luminaire. Increased exposure risk to facility personnel may be present depending upon the number of horticultural luminaires and their placement and/or positioning within the plant growth facility. It is the responsibility of the plant growth facility to address these risks at the facility level and to ensure that people entering the plant growth areas while the lights are on, are aware of these risks and that appropriate safeguards are in place. **Nevertheless, avoid unnecessary long irradiation and looking directly into the light source.**

Distance to illuminated object

The distance between the LED-light (lower edge of the light) and the illuminated surface or the illuminated object must be at least 15cm.

Scope of application of the light

The SANlight EVO LED-light is only suitable for illuminating plants, even in wet indoor areas.

Permissible ambient temperature for operation

The SANlight EVO LED-light can be operated up to a maximum ambient temperature of 35°C. The minimum ambient temperature at which the SANlight EVO LED-light can be operated is 5°C.

Permissible ambient conditions for operation

The SANlight EVO LED-light may be operated up to a max. relative humidity of 90% (non-condensing).

Required accessories for hanging the lamp

No hanging accessories are included in the scope of delivery. The EVO lamp may only be hung with sufficient load-bearing suspensions. It is recommended that the lights are suspended from the suspension eyes using steel carabiners and ropes. (see figures 1, 2 and 3) The suspension must withstand a permanent load of at least 8 kg.

Permissible orientation of the LED-light

The SANlight EVO LED-light may only be operated in a horizontally suspended position. In this case, a minimum distance to surrounding objects of 15cm must be observed. In order to guarantee the correct position, the light must be suspended from both suspension eyelets. (see Figures 1 and 2) The light may also be suspended via the outer suspension eyelets, in order to achieve an inclined position of the light. See Figure 3.

Laying the cables

When laying any cables, make sure that they are strain-relieved. Under no circumstances should cables be subjected to tension. The cables must be unwound. The EVO light must not be operated with rolled-up cables. Make sure, that they are not concealed or extended through a wall, floor, ceiling or other parts of the building. Also do not locate the cables above a suspended ceiling and make sure that they are not permanently affixed to the building structure. Note, that they are laid in such a way that they are not exposed to stress and are protected from physical damage. Cables must also be visible along their entire length. Notice, that the maximum ambient temperature for running the EVO LED-light with the cable is 35°C.

Maintenance and Cleaning

To clean the LED-light, use a dust and grease-free cloth. The lamp must be disconnected from the mains for cleaning. Never use other aids such as cleaning agents, damp cloths etc. Make sure that the secondary optics of the LEDs are not scratched by cleaning.

Works and Repairs

Repairs and works may only be carried out by the manufacturer. If repairs, modifications and other works are not performed by the manufacturer, the manufacturer's warranty and product liability expire.

Upgrade Service

The individual LED-modules can be exchanged by qualified personnel. Please contact the certified SANlight dealer of trust.

Guarantee Policy

This device has been designed, manufactured and tested in accordance with the European safety standard (EN60598/CE). The guarantee for the LED-light and accessories is 3 years from the date of purchase.

The guarantee does not apply to equipment that has not been installed and maintained as specified in this manual. The manufacturer assumes no responsibility for damage caused by unauthorized or incorrect use. In case of damage, the device (LED-light incl. connecting cable) must be returned to the respective SANlight sales partner, from whom the product was purchased. They send the defective goods to the manufacturer, SANlight. After repair by the manufacturer, the device is returned to the respective sales partner.

Hazard warnings Avertissements de danger

Attention: The minimum distance to objects in the vicinity of the LED-light is 15cm. The heat sink/housing must not be covered. La distance minimale aux objets à proximité de la lumière LED est de 15 cm. Le dissipateur thermique / boîtier ne doit pas être couvert. **Attention:** The SANlight EVO LED-light is only suitable for illuminating plants, even in wet indoor areas. La lumière LED EVO ne peut être utilisée que pour éclairer des plantes, même dans des zones intérieures humides. **WARNING: POSSIBLE RISK OF INJURY TO EYES AND SKIN:** Hazardous optical radiation may be emitted from the light source. Do not stare at operating light source. May be harmful to the eyes. UV may be emitted from the light source. Eye or skin irritation may result from exposure. Use appropriate shielding. IR may be emitted from the light source. Do not stare at operating light source. RISQUE DE BLESSURE POSSIBLE AUX YEUX ET À LA PEAU: Un rayonnement optique dangereux peut être émis par la source lumineuse. Ne regardez pas la source lumineuse quand elle est allumée. Peut être nocif pour les yeux. La source lumineuse peut émettre des rayons UV. L'exposition peut provoquer une irritation des yeux ou de la peau. Utilisez un écran approprié. La source lumineuse peut émettre des rayons infrarouges. Ne regardez pas la source lumineuse quand elle est allumée. **Attention:** Do not operate in a potentially explosive atmosphere. Ne pas utiliser dans une atmosphère potentiellement explosive. **Attention:** The EVO LED-light may reach temperatures of up to 70°C at the maximum ambient temperature (35°C). La lampe LED EVO peut atteindre des températures allant jusqu'à 70 ° C à la température ambiante maximale (35°C). **Attention:** The LED-light must be sufficiently secured against falling. La lumière LED doit être suffisamment sécurisée contre les chutes. **Attention:** If damage to the LED-light or a cable is found, the light must be taken out of service immediately. This must be done by disconnecting the light from the mains supply. En cas de dommage à la lumière LED ou à un câble, la lumière doit être immédiatement mise hors service. Cela doit être fait en déconnectant la lumière de l'alimentation secteur. **Attention:** To avoid hazards, a damaged outer flexible cable of this light may only be replaced by the manufacturer, their service representative or a comparable specialist. Pour éviter tout danger, un câble flexible extérieur endommagé de cette lampe ne peut être remplacé que par le fabricant, son technicien de maintenance ou un spécialiste comparable. **Attention:** The light source cannot be obtained separately. La source lumineuse ne peut pas être obtenue séparément. **Attention:** To protect against injuries, appropriate personal protective equipment (PPE) must be worn when working in the area of the lamp. Pour vous protéger contre les blessures, vous devez porter un équipement de protection individuelle (EPI) approprié lorsque vous travaillez dans la zone de la lampe. **Attention:** The models of the EVO-Series are NOT designed for looping through the mains supply. Les modèles de la série EVO ne sont PAS conçus pour faire une boucle sur le secteur.

Scope of Delivery

Figure 4 shows all the components of your EVO LED-light. Please check the contents of the packaging for completeness and damage. Never use damaged components. The mains connection cable is not included and can be ordered separately from your dealer. The scope of delivery includes: 1 x EVO LED-light, Operating instructions.

Installation and Assembly Instructions

Fixing and suspension of the SANlight EVO LED-light: The EVO LED-light can be suspended from the suspension eyelets (see Figures 1, 2 and 3). When suspending the LED-light, a safety distance of 15 cm to surrounding objects must be observed. Make sure that your suspension is secure and secure the light against accidentally falling.

EVO electrical connection: The EVO LED-light must be connected to the power supply via a separately available SANlight connection cable (see table 1) . It is possible to connect each light separately or to connect several lights in parallel to each other. For both options SANlight cables must be used.

Electrical connection of one single EVO lamp: To connect each lamp by a separate power cable the following country specific cables can be used. First connect the cable to the lamp, before connecting to the grid.

	SANlight article number	description	properties	socket
Table 1	AI0037	Grid power cable EVO-Series EU	2m, PVC, AWG 16, black	Euro plug
	AI0038	Grid power cable EVO-Series UK	2m, PVC, AWG 16, black	UK plug
	AI0039	Grid power cable EVO-Series CH	2m, PVC, AWG 16, black	Switzerland plug SEV1011
	AI0040	Grid power cable EVO-Series US	2m, PVC, AWG 16, black	US plug NEMA 5-15 P

Connecting several lamps

Depending on the circuit breaker different numbers of EVO LED-lights can be connected to one power socket. Please check table 1.

Powerline fuse protection

Circuit breaker Typ B 230V
Circuit breaker Typ C 230V

Number of lights per circuit breaker

4 lamps
7 lamps

For connecting more as 7 lamps an inrush current protector has to be used. To connect several lamps to one power socket the following items are needed.

SANlight article number	description	quantity
AI0037 / AI0038 / AI0039 / AI0040	Grid power cable Q-Series Gen2 2m, PVC, AWG 16, black	1
AI0018	H distribution block	1 pcs. for 2 lamps
AI0022	Cable extension 1m, PVC, AWG 16, black	1 pcs. per lamp

Attention: Connecting several lamps to one power socket must be done by skilled staff. Please contact your certified SANlight trading partner. Check our website www.sanlight.com for detailed instructions.

Tec. Specifications EVO 3-60, EVO 3-80 and EVO 3-100

Mains power consumption	200W
Input voltage	220-240V~ 50/60Hz
Permissible ambient temperature	5-35°C

Tec. Specifications EVO 4-80, EVO 4-100 and EVO 4-120

Mains power consumption	265W
Input voltage	220-240V~ 50/60Hz
Permissible ambient temperature	5-35°C

Technical Specifications EVO 5-100, EVO 5-120 and EVO 5-150

Mains power consumption	340W
Input voltage	220-240V~ 50/60Hz
Permissible ambient temperature	5-35°C

Tec. Specifications EVO 6-120 and EVO 6-150

Mains power consumption	400W
Input voltage	220-240V~ 50/60Hz
Permissible ambient temperature	5-35°C

For the position of the Tc measuring point see marking in figure 5.

Technical Specifications of a single LED-module

Operating current	0,73A (DC)
Power	63W
Operating voltage	86V (DC)
Tc	105°C



Attention: Do not look directly into the light source. Ne regardez pas directement dans la source lumineuse.
"照明器具を長時間見続けることがないように照明器具を設置すること"



The LED-light must not be disposed of in household waste! For disposal, the light can be handed back to the manufacturer. The disposal costs are borne by the manufacturer. Alternatively, the light can be delivered to a disposal company for electrical appliances. La lampe LED ne doit pas être jetée avec les ordures ménagères! Pour l'élimination, la lumière peut être restituée au fabricant. Les coûts d'élimination sont à la charge du fabricant. Alternativement, la lumière peut être livrée à une entreprise d'élimination des appareils électriques.



Attention: The light is not suitable for covering! La lumière n'est pas adaptée pour couvrir!



Caution: Risk of shock. Disconnect power before relamping. Attention: Risque d'électrocution. Débrancher l'alimentation avant de remplacer la lampe.

IP65

Dustproof and jet-proof luminaire. Antipoussière et protégé contre les jets d'eau sous tous les angles.



The light source of this light may only be replaced by the manufacturer or a service technician appointed by him or a similarly qualified person. La source lumineuse de cet éclairage ne peut être remplacée que par le fabricant ou un technicien de maintenance désigné par lui ou une personne de qualification similaire.



Figure 1



Figure 2



Figure 3



Figure 4




Figure 5

By purchasing the SANlight EVO LED-light you have decided on a high-quality product, which will give you much pleasure. Please read the operating instructions before using your EVO LED-light, as incorrect use can cause damage to the light or to humans/animals/plants. Failure to use the EVO properly will void any manufacturer's warranty and product liability.

Valid for **EVO 3-60, EVO 3-80, EVO 3-100, EVO 4-80, EVO 4-100, EVO 4-120, EVO 5-100, EVO 5-120, EVO 5-150, EVO 6-120, EVO 6-150** further denoted as **EVO**.

ATTENTION: Photobiological safety note:

According to DIN EN 62471, the EVO LED-module corresponds to risk group "exempt". These photobiological safety markings are based on testing of the light output characteristic of a single horticultural luminaire. Increased exposure risk to facility personnel may be present depending upon the number of horticultural luminaires and their placement and/or positioning within the plant growth facility. It is the responsibility of the plant growth facility to address these risks at the facility level and to ensure that people entering the plant growth areas while the lights are on, are aware of these risks and that appropriate safeguards are in place. **Nevertheless, avoid unnecessarily long irradiation and looking directly into the light source.**

Distance to illuminated object

The distance between the LED-light (lower edge of the light) and the illuminated surface or the illuminated object must be at least 15cm.

Scope of application of the light

The SANlight EVO LED-light is only suitable for illuminating plants, even in wet indoor areas.

Permissible ambient temperature for operation

The SANlight EVO LED-light can be operated up to a maximum ambient temperature of 35°C. The minimum ambient temperature at which the SANlight EVO LED-light can be operated is 5°C.

Permissible ambient conditions for operation

The SANlight EVO LED-light may be operated up to a max. relative humidity of 90% (non-condensing).

Required accessories for hanging the lamp

No hanging accessories are included in the scope of delivery. The EVO lamp may only be hung with sufficient load-bearing suspensions. It is recommended that the lights are suspended from the suspension eyes using steel carabiners and ropes. (see figures 1, 2 and 3) The suspension must withstand a permanent load of at least 8 kg.

Permissible orientation of the LED- light

The SANlight EVO LED-light may only be operated in a horizontally suspended position. In this case, a minimum distance to surrounding objects of 15cm must be observed. In order to guarantee the correct position, the light must be suspended from both suspension eyelets. (see Figures 1 and 2) The light may also be suspended via the outer suspension eyelets, in order to achieve an inclined position of the light. See Figure 3.

Laying the cables

When laying any cables, make sure that they are strain-relieved. Under no circumstances should cables be subjected to tension. The cables must be unwound. The EVO light must not be operated with rolled-up cables. Make sure, that they are not concealed or extended through a wall, floor, ceiling or other parts of the building. Also do not locate the cables above a suspended ceiling and make sure that they are not permanently affixed to the building structure. Note, that they are laid in such a way that they are not exposed to stress and are protected from physical damage. Cables must also be visible along their entire length. Notice, that the maximum ambient temperature for running the EVO LED-light with the cable is 35°C.

Maintenance and Cleaning

To clean the LED-light, use a dust and grease-free cloth. The lamp must be disconnected from the mains for cleaning. Never use other aids such as cleaning agents, damp cloths etc. Make sure that the secondary optics of the LEDs are not scratched by cleaning.

Works and Repairs

Repairs and works may only be carried out by the manufacturer. If repairs, modifications and other works are not performed by the manufacturer, the manufacturer's warranty and product liability expire.

Upgrade Service

The individual LED-modules can be exchanged by qualified personnel. Please contact the certified SANlight dealer of trust.

Guarantee Policy

This device has been designed, manufactured and tested in accordance with the European safety standard (EN60598/CE). The guarantee for the LED-light and accessories is 3 years from the date of purchase.

The guarantee does not apply to equipment that has not been installed and maintained as specified in this manual. The manufacturer assumes no responsibility for damage caused by unauthorized or incorrect use. In case of damage, the device (LED-light incl. connecting cable) must be returned to the respective SANlight sales partner, from whom the product was purchased. They send the defective goods to the manufacturer, SANlight. After repair by the manufacturer, the device is returned to the respective sales partner.

Hazard warnings Avertissements de danger

Attention: The minimum distance to objects in the vicinity of the LED-light is 15cm. The heat sink/housing must not be covered. La distance minimale aux objets à proximité de la lumière LED est de 15 cm. Le dissipateur thermique / boîtier ne doit pas être couvert. **Attention:** The SANlight EVO LED-light is only suitable for illuminating plants, even in wet indoor areas. La lumière LED EVO ne peut être utilisée que pour éclairer des plantes, même dans des zones intérieures humides. **WARNING: POSSIBLE RISK OF INJURY TO EYES AND SKIN:** Hazardous optical radiation may be emitted from the light source. Do not stare at operating light source. May be harmful to the eyes. UV may be emitted from the light source. Eye or skin irritation may result from exposure. Use appropriate shielding. IR may be emitted from the light source. Do not stare at operating light source. RISQUE DE BLESSURE POSSIBLE AUX YEUX ET À LA PEAU: Un rayonnement optique dangereux peut être émis par la source lumineuse. Ne regardez pas la source lumineuse quand elle est allumée. Peut être nocif pour les yeux. La source lumineuse peut émettre des rayons UV. L'exposition peut provoquer une irritation des yeux ou de la peau. Utilisez un écran approprié. La source lumineuse peut émettre des rayons infrarouges. Ne regardez pas la source lumineuse quand elle est allumée. **Attention:** Do not operate in a potentially explosive atmosphere. Ne pas utiliser dans une atmosphère potentiellement explosive. **Attention:** The EVO LED-light may reach temperatures of up to 70°C at the maximum ambient temperature (35°C). La lampe LED EVO peut atteindre des températures allant jusqu'à 70 ° C à la température ambiante maximale (35°C). **Attention:** The LED-light must be sufficiently secured against falling. La lumière LED doit être suffisamment sécurisée contre les chutes. **Attention:** If damage to the LED-light or a cable is found, the light must be taken out of service immediately. This must be done by disconnecting the light from the mains supply. En cas de dommage à la lumière LED ou à un câble, la lumière doit être immédiatement mise hors service. Cela doit être fait en déconnectant la lumière de l'alimentation secteur. **Attention:** To avoid hazards, a damaged outer flexible cable of this light may only be replaced by the manufacturer, their service representative or a comparable specialist. Pour éviter tout danger, un câble flexible extérieur endommagé de cette lampe ne peut être remplacé que par le fabricant, son technicien de maintenance ou un spécialiste comparable. **Attention:** The light source cannot be obtained separately. La source lumineuse ne peut pas être obtenue séparément. **Attention:** To protect against injuries, appropriate personal protective equipment (PPE) must be worn when working in the area of the lamp. Pour vous protéger contre les blessures, vous devez porter un équipement de protection individuelle (EPI) approprié lorsque vous travaillez dans la zone de la lampe. **Attention:** The models of the EVO-Series are NOT designed for looping through the mains supply. Les modèles de la série EVO ne sont PAS conçus pour faire une boucle sur le secteur.

Scope of Delivery

Figure 4 shows all the components of your EVO LED-light. Please check the contents of the packaging for completeness and damage. Never use damaged components. The mains connection cable is not included and can be ordered separately from your dealer. The scope of delivery includes: 1 x EVO LED-light, Operating instructions.

Installation and Assembly Instructions

Fixing and suspension of the SANlight EVO LED-light: The EVO LED-light can be suspended from the suspension eyelets (see Figures 1, 2 and 3). When suspending the LED-light, a safety distance of 15 cm to surrounding objects must be observed. Make sure that your suspension is secure and secure the light against accidentally falling.

EVO electrical connection: The EVO LED-light must be connected to the power supply via a separately available SANlight connection cable (see table 1) . It is possible to connect each light separately or to connect several lights in parallel to each other. For both options SANlight cables must be used.

Electrical connection of one single EVO lamp: To connect each lamp by a separate power cable the following country specific cables can be used. First connect the cable to the lamp, before connecting to the grid.

	SANlight article number	description	properties	socket
Table 1	AI0037	Grid power cable EVO-Series EU	2m, PVC, AWG 16, black	Euro plug
	AI0038	Grid power cable EVO-Series UK	2m, PVC, AWG 16, black	UK plug
	AI0039	Grid power cable EVO-Series CH	2m, PVC, AWG 16, black	Switzerland plug SEV1011
	AI0040	Grid power cable EVO-Series US	2m, PVC, AWG 16, black	US plug NEMA 5-15 P

Connecting several lamps

Depending on the circuit breaker different numbers of EVO LED-lights can be connected to one power socket. Please check table 1.

Powerline fuse protection

Circuit breaker Typ B 230V
Circuit breaker Typ C 230V

Number of lights per circuit breaker

4 lamps
7 lamps

For connecting more as 7 lamps an inrush current protector has to be used. To connect several lamps to one power socket the following items are needed.

SANlight article number	description	quantity
AI0037 / AI0038 / AI0039 / AI0040	Grid power cable Q-Series Gen2 2m, PVC, AWG 16, black	1
AI0018	H distribution block	1 pcs. for 2 lamps
AI0022	Cable extension 1m, PVC, AWG 16, black	1 pcs. per lamp

Attention: Connecting several lamps to one power socket must be done by skilled staff. Please contact your certified SANlight trading partner. Check our website www.sanlight.com for detailed instructions.

Tec. Specifications EVO 3-60, EVO 3-80 and EVO 3-100

Mains power consumption	200W
Input voltage	120/277V~ 50/60Hz
Permissible ambient temperature	5-35°C

Tec. Specifications EVO 4-80, EVO 4-100 and EVO 4-120

Mains power consumption	265W
Input voltage	120/277V~ 50/60Hz
Permissible ambient temperature	5-35°C

Technical Specifications EVO 5-100, EVO 5-120 and EVO 5-150

Mains power consumption	340W
Input voltage	120/277V~ 50/60Hz
Permissible ambient temperature	5-35°C

Tec. Specifications EVO 6-120 and EVO 6-150

Mains power consumption	400W
Input voltage	120/277V~ 50/60Hz
Permissible ambient temperature	5-35°C

For the position of the Tc measuring point see marking in figure 5.

Technical Specifications of a single LED-module

Operating current	0,73A (DC)
Power	63W
Operating voltage	86V (DC)
Tc	105°C



Attention: Do not look directly into the light source. Ne regardez pas directement dans la source lumineuse.
"照明器具を長時間見続けることがないように照明器具を設置すること"



The LED-light must not be disposed of in household waste! For disposal, the light can be handed back to the manufacturer. The disposal costs are borne by the manufacturer. Alternatively, the light can be delivered to a disposal company for electrical appliances. La lampe LED ne doit pas être jetée avec les ordures ménagères! Pour l'élimination, la lumière peut être restituée au fabricant. Les coûts d'élimination sont à la charge du fabricant. Alternativement, la lumière peut être livrée à une entreprise d'élimination des appareils électriques.



Attention: The light is not suitable for covering! La lumière n'est pas adaptée pour couvrir!



Caution: Risk of shock. Disconnect power before relamping. Attention: Risque d'électrocution. Débrancher l'alimentation avant de remplacer la lampe.

IP65

Dustproof and jet-proof luminaire. Antipoussière et protégé contre les jets d'eau sous tous les angles.



The light source of this light may only be replaced by the manufacturer or a service technician appointed by him or a similarly qualified person. La source lumineuse de cet éclairage ne peut être remplacée que par le fabricant ou un technicien de maintenance désigné par lui ou une personne de qualification similaire.




Figure 1



Figure 2



Figure 3



Figure 4




Figure 5